

HOW TO USE THE S+ SLOT SET DENOMINATION AND CLEAR CHIPS

1. OPEN THE DOOR, TURN THE MACHINE OFF,
REMOVE THE COIN TRAY AND THE HOPPER.
2. REMOVE THE MAIN COMPUTER BOARD (MPU) BY TUGGING
THE BLACK HANDLE UPWARD UNTIL THE BOARD IS FREE
FROM THE CONECTORS ON THE BACKPLANE BOARD.

****NOTE** YOU WILL BE WORKING WITH STATIC SENSITIVE
IC CHIPS AND YOU MUST DISCHARGE ANY STATIC FROM YOUR
BODY BY TOUCHING THE METAL SHELL INSIDE THE MACHINE
BEFORE CONTINUING.**
3. REMOVE THE GAME PROM CHIP FROM IT'S SOCKET BY PRYING
IT UP GENTLY WITH A SMALL FLAT BLADE SCREWDRIVER -
BEING CAREFUL NOT TO BEND ANY PINS.
NOTE THE NOTCH ON ONE END OF THE CHIP. WHEN YOU ARE
INSTRUCTED TO PLUG IT BACK IN MAKE SURE IT'S NOTCH
IS FACING THE SAME WAY AS THE NOTCH ON THE SOCKET.
PLACE THE REMOVED GAME PROM INTO THE CONDUCTIVE FOAM
THAT CAME WITH THE SET AND CLEAR CHIPS.
4. PLUG IN THE CLEAR CHIP - MAKE SURE THE NOTCH IS
FACING THE CORRECT WAY (MATCHING THE NOTCH ON THE
SOCKET) AND MAKE SURE YOU DON'T BEND ANY PINS.
5. PLUG THE COMPUTER BOARD BACK INTO THE BACKPLANE
BOARD AND MAKE SURE IT IS SEATED PROPERLY.
6. YOU DO NOT NEED TO INSTALL THE HOPPER OR COIN TRAY
FOR THIS NEXT STEP.

-CLEARING THE MPU BOARD-
7. TURN ON THE MACHINE, LEAVE THE DOOR OPEN.
NO REELS WILL SPIN. YOU WILL HEAR ONE DING
PRESS AND HOLD IN THE WHITE TEST BUTTON UNTIL YOU
HEAR 2 DINGS THEN RELEASE THE WHITE TEST BUTTON.
WATCH FOR A 999 ON THE CREDIT DISPLAY THEN TURN THE
MACHINE OFF.

-SETTING UP INITIAL GAME OPTIONS-
8. REMOVE THE MPU BOARD AND REMOVE THE CLEAR CHIP AND
PLACE IT BACK INTO THE CONDUCTIVE FOAM.
9. INSTALL THE ORIGINAL GAME PROM CHIP. MAKE SURE THE
NOTCH IS FACING THE CORRECT WAY AND NO PINS ARE BENT.
INSTALL THE MPU BOARD BACK INTO THE MACHINE.
- A. PLUG THE HOPPER BACK IN.
LEAVE THE DOOR OPEN AND TURN THE MACHINE BACK ON.
THE REELS WILL SPIN THEN STOP.
AFTER A WHILE YOU WILL SEE A "61" CODE ON THE DISPLAY.
PRESS AND HOLD THE WHITE TEST BUTTON AND THE 61

WILL CHANGE TO A 61-1.
CLOSE THE MACHINE DOOR AND TURN THE JACKPOT RESET KEY ONCE. THE MACHINE WILL EITHER INITILIZE WITH A REEL SPIN OR A 65-1 WILL APPEAR ON THE DISPLAY. IF A 65-1 SHOWS OPEN THE DOOR AND PRESS THE WHITE TEST BUTON AGAIN THEN FOR 2 SECONDS. THE METERS WILL GO BLANK THEN THE REELS WILL SPIN.
RE-CLOSE THE DOOR. WAIT FOR THE "INSERT COIN" LIGHT TO COME ON.
IF YOU DON'T HAVE A BILL VALIDATOR THE COIN TRAY CAN ALSO BE RE-INSTALLED.

-SETTING CREDIT MODE AND DENOMINATION-

- B. OPEN THE DOOR AND REPEAT PRESSING THE WHITE TEST BUTTON UNTIL YOU SEE A 5--0, 5--1 ON THE DISPLAY.
TAP THE SPIN BUTTON UNTIL A 5--2 IS SEEN THEN STOP.
PRESS THE TEST BUTTON UNTIL A "6" IS SEEN ON THE DISPLAY.
TAP THE SPIN BUTTON UNTIL THE DENOMINATION OF YOUR MACHINE IS SEEN ON THE CREDIT DISPLAY.
CONTINUE PRESSING THE TEST BUTTON UNTIL ALL DISPLAYS BLANK OUT. AFTER THE REELS STOP SPINNING CLOSE THE DOOR AND THE GAME IS READY FOR PLAY.
***NOTE** WHILE STEPPING THROUGH THE TEST BUTTON FUNCTIONS YOU MAY HAVE NOTICED A SECTION WHERE A 1000 IS SHOWN WITH THE ONES DIGIT IS FLASHING. THIS IS YOUR INITIAL CREDIT LIMIT. YOU CAN CHANGE THIS VALUE TO 9999 BY TAPPING THE SPIN BUTTON TO INCREASE EACH DIGIT TO 9. STEPPING THROUGH THE DIGITS BY TURNING THE JACKPOT RESET KEY. THE FIRST TWO 1000'S ARE THE ONES THAT SHOULD BE CHANGED TO 9999.*

-BILL VALIDATOR INITIALIZATION USING THE SET CHIP-

- C. TURN POWER OFF AND REMOVE THE HOPPER AND MPU BOARD.
REMOVE THE GAME PROM AND INSTALL THE SET DENOMINATION CHIP. RE-INSTALL THE MPU BOARD AND TURN POWER ON.
PRESS THE TEST BUTTON ONE TIME.
A 9--0 WILL SHOW ON THE DISPLAY. TAP THE SPIN BUTTON TO MAKE THE 9--0 A 9--1. PRESS THE TEST BUTTON ONCE THEN TAP THE SPIN BUTTON UNTIL UNTIL THE DENOMINATION OF YOUR MACHINE IS SEEN THEN HOLD THE WHITE TEST BUTTON IN UNTIL THE DISPLAY BLANKS OUT AND A ZERO IS SEEN. THIS STORES YOUR SETTINGS INTO MEMORY.
- D. TURN POWER OFF AND REMOVE THE MPU BOARD.
REMOVE THE SET CHIP AND RE-INSTALL THE GAME PROM CHIP.
RE-ASSEMBLE THE MACHINE WITH THE HOPPER AND COIN TRAY. TURN THE MACHINE BACK ON LEAVING THE DOOR OPEN.
FOLLOW STEP "A" ABOVE TO CLEAR THE "61" AND "61-1" CODES THAT COME UP.
THE GAME IS READY FOR PLAY AND WILL NOW TAKE BILLS.